

	FL122040-HB-BR-2	FL195040-HB-BR-2
Jmenovitý příkon (W)	20	50
Světelný tok svítidla (lm)	2000	5000
Světelný tok LED zdroje (lm)	2000	5000
Vstupní napětí (V)	230	230
Barevná teplota (K)	4000	4000
CRI	80	80
PF	0,7	0,7
Provozní teplota	-20°C až 40°C	-20°C až 40°C
Krytí IP	IP44	IP44
Životnost	25000 hod	25000 hod
Rozměry [VxŠxH](mm)	285x230x60	300x260x55
Hmotnost (g)	650	1090
Délka přívodního kabelu (m)	1,5	1,5

Návod k obsluze

Přenosné TESLA LED reflektory FL122040-HB-BR-2 a FL195040-HB-BR-2 s polohovatelným stojánkem opatřeným pěnou na rukojeti a dolní částí stojanu jsou ideálním zdrojem světla při pracovních aktivitách, díky typu LED diod a mléčnému difuzoru jejich uspořádání osvětluje široký prostor (jedná se o širokoúhlé reflektory). Sklon reflektoru je možné upravit pro optimální úhel nasvícení požadovaného místa nebo plochy.

- 1) Umístěte svítidlo na požadované místo a upravte sklon rukojeti stojáčku a reflektoru na stojáčku, aby dosáhli optimálního úhlu nasvícení. Zajistěte, že svítidlo je vzdáleno nejméně 1 metr od osvětlovaného objektu. Pokud je svítidlo umístěno v rohu, ujistěte se, že je od stěn vzdáleno nejméně 20 cm, aby bylo zajištěno chlazení okolním vzduchem. Nepřekrývejte svítidlo a neumísťujte ho do malých a těsných prostorů, kde je omezený přísun vzduchu a nedostatečné chlazení. Svítidlo nesmí být používáno v prostředí s rizikem výbuchu nebo požáru.
- 2) Před připojením napájecího kabelu ke zdroji el. napětí zkontrolujte, zda hodnota napájecího napětí na štítku přístroje odpovídá hodnotě napětí v zásuvce.
- 3) Vidlici přívodního kabelu zasuňte do zásuvky s elektrickým napětím.
- 4) Zapnutí svítidla je probíhá zapojením do elektrické sítě.
- 5) Vypnutí proveďte vypojením z elektrické sítě.

Čištění / údržba

Lampa se může při zapnutí velmi zahřát, proto ji před čištěním vždy nechte zcela vychladnout. Před čištěním vypněte napájení. Čištěte suchým hadříkem, nepoužívejte agresivní čisticí prostředky nebo ostré nástroje. Neponořujte reflektor do vody!



Nevyhazujte elektrické spotřebiče jako netříděný komunální odpad, použijte sběrná místa tříděného odpadu. Pro aktuální informace o sběrných místech kontaktujte místní úřady. Pokud jsou elektrické spotřebiče uloženy na skládkách odpadků, nebezpečné látky mohou prosakovat do podzemní vody a dostat se do potravního řetězce a poškozovat vaše zdraví. TESLA lighting prohlašuje, že tento produkt je ve shodě se základními požadavky a dalšími příslušnými ustanoveními směrnice. Zařízení lze volně používat v rámci EU.



Výrobek splňuje
požadavky EU



Tento výrobek je v souladu s Evropskou směrnicí 2017/369/EU.
Aktuální verzi manuálu najdete vždy na www.tesla-lighting.cz

Výrobce si vyhrazuje právo změn parametrů, vzhledu, tvaru či vlastností produktu nebo obalu. Stejně tak i tohoto dokumentu.



Výrobce:
TESLA lighting s.r.o.
Mladoboleslavská 1108/6,
197 00 Praha 9, Česká Republika, EU



FL122040-HB-BR-2 | FL195040-HB-BR-2



Vážený zákazníku
děkujeme Vám za zakoupení našeho produktu. Pozorně si přečtěte následující pokyny a dodržujte je.
Předejdete tak jeho nesprávnému použití či poškození. Tento návod pečlivě uchovejte



BEZPEČNOSTNÍ POKYNY

Výrobce ani prodejce neodpovídají za vady způsobené nesprávným použitím produktu

- Nesprávné elektrické připojení a/nebo příliš vysoké síťové napětí mohou vést k úrazu elektrickým proudem.
- V případě poškození okamžitě odpojte produkt ze sítě.
- Údržbu a opravy musí být provedené odborníkem, jinak vyprší záruka.
- Používejte lampu pouze k určenému účelu. Technické změny nejsou povoleny.
- Reflektor nikdy nezakrývejte! Hořlavý! Uchovávejte mimo dosah otevřeného ohně a horkých povrchů.
- Minimální vzdálenost reflektoru od osvětlované plochy je $> 0,5$ m
- Reflektor a jeho příslušenství obsahují malé díly. Držte mimo dosah dětí.



Nebezpečí úrazu elektrickým proudem!
 Nepoužívat jsou-li světelné zdroje poškozené.



Technical parameters

	FL122040-HB-BR-2	FL195040-HB-BR-2
Power input (W)	20	50
Luminous flux (lm)	2000	5000
PCB lumen output (lm)	2000	5000
Input voltage (V)	230	230
Color temperature (K)	4000	4000
CRI	80	80
PF	0,7	0,7
Operating temperature	-20°C to 40°C	-20°C to 40°C
IP protection	IP44	IP44
Lifetime	25000 hod	25000 hod
Dimensions [HxWxD](mm)	285x230x60	300x260x55
Weight (g)	650	1090
Length of the supply cable (m)	1,5	1,5

This product contains a light source of energy efficiency class <F>.

Instructions for use

Portable TESLA LED floodlights FL122040-HB-BR-2 and FL195040-HB-BR-2 with adjustable stand equipped with foam on the handle and bottom of the stand are an ideal source of light during work activities, thanks to the type of LEDs and milk diffuser, their arrangement illuminates a wide area (these are wide-angle reflectors). The inclination of the reflector can be adjusted for an optimal angle of illumination of the desired place or area.

- 1) Place the luminaire in the desired location and adjust the inclination of the stand handle and reflector on the stand to achieve the optimal lighting angle. Ensure that the luminaire is at least 1 meter away from the illuminated object. If the luminaire is placed in the corner, make sure that it is at least 20 cm away from the walls to ensure cooling by the ambient air. Do not overlap the luminaire and place it in small and tight spaces where there is limited air supply and insufficient cooling. The luminaire must not be used in an environment with a risk of explosion or fire.
- 2) Before connecting the power cord to a power source check that the supply voltage value on the label The device corresponds to the voltage value in the socket.
- 3) Plug the plug of the power cable into the socket with el. Voltage.
- 4) Switching on the luminaire is by connecting it to the electrical network.
- 5) Switch off by unplugging from the mains.

Cleaning / maintenance

The lamp can get very hot when switched on, so always let it cool completely before cleaning. Turn off the power before cleaning. Clean with a dry cloth, do not use aggressive cleaning agents or sharp tools. Do not immerse the reflector in water!

Package content

- LED reflector
- User manual



Do not dispose of electrical appliances as unsorted municipal waste, use the collection points for sorted waste. Contact your local authorities for up-to-date information on collection points. If electrical appliances are stored in landfills, hazardous substances can seep into groundwater and enter the food supply chain and harm your health. TESLA lighting declares that this product is in compliance with the basic requirements and other relevant provisions of the directive. The device can be used freely within the EU.



The product complies
EU requirements



This product complies with European Directive 2017/369/EU.
Current version of the manual at www.tesla-lighting.eu

The manufacturer reserves the right to change the parameters, appearance, shape or properties of the product or packaging.



Manufacturer:
TESLA lighting s.r.o.
Mladoboleslavská 1108/6,
197 00 Praha 9, Česká Republika, EU



USER MANUAL

LED FLOODLIGHT

FL122040-HB-BR-2 | FL195040-HB-BR-2



Dear customer

Thank you for purchasing our product. Please read the following instructions carefully and follow them.
This will prevent its incorrect use or damage. Keep this manual carefully



SAFETY INSTRUCTIONS

Neither the manufacturer nor the seller is responsible for defects caused by improper use of the product

- Incorrect electrical connection and/or too high mains voltage can lead to electric shock.
- In case of damage, immediately disconnect the product from the mains.
- Maintenance and repairs must be carried out by a specialist, otherwise the warranty will expire.
- Use the lamp only for its intended purpose. Technical changes are not permitted.
- Never cover the floodlight! Flammable! Keep away from open flames and hot surfaces.
- The minimum distance between the floodlight and the illuminated surface is > 0.5 m
- The floodlight and its accessories contain small parts. Keep out of reach of children.
- The manufacturer/distributor of the device rejects all claims for damages and injuries, caused by improper installation or use.



Risk of electric shock!

▲ Do not use if light sources are damaged.